



Temporary Power

By Midwest Electric Company

Midwest Electric provides the temporary power needed by construction trades prior to permanent service equipment installation. Having this equipment on the job site eliminates concerns about safety, theft, vandalism, weather, nuisance tripping, durability and code violations.

These units come to the construction job site ready to work. They are completely factory assembled, factory wired, and factory tested. The only thing you need to do is mount them and make the electrical connection.

FEATURES AND BENEFITS

Rugged Durability

- NEMA 3R enclosure has padlock provision
- Rolled edge door protects cords
- Continuous duty meter socket with meter guides and reinforced jaws (ringless and ring type)
- Accepted meter sealing accommodations
- G90 galvanized steel construction for superior corrosion protection
- Durable polyester powder coat finish resists chipping and fading
- Meets latest National Electrical Code and OSHA requirements

User Safety

- Dead front construction prevents accidental contact with live parts
- Padlock provision to prevent unauthorized access

Installation Ease

- Factory wired and assembled components reduce installation time
- Removable door has stay-open position
- All terminals accept copper or aluminum wire
- Wide range of most common configurations
- Broad range of concentric knockouts accommodate wiring needs
- All units are supplied with a factory installed Cu/Al equipment ground lug








SELECTION

All models are cULus listed, are suitable for use on 120/240V, single phase 3-wire systems and have hub openings.






Metered

Overhead/Underground Feed

Model Number	Receptacle	Circuit Protection	Amps	Spaces	Wire Range	Cabinet Size	Load Center Interior	Diagram	Unit Wt.	Std. Pkg.	UL Approved
M138CB2033	6-20R, (2) 5-20R2GFCI	THQL21100, (2) THQL1120, THQL2120GFT	100	2	A	14 x 26	LC88PC		42	1	UL
R101CB2010	5-20R2GFCI	THQL21100, THQL1120		5					38		
R111CB2010	(2) 5-20R2GFCIWR	THQL21100, (2) THQL1120		4					40		
R138CB2033	6-20R, (2) 5-20R2GFCIWR	THQL21100, (2) THQL1120, THQL2120GFT		2					41		
R176CB2033	14-50WR, (2) 5-20R2GFCIWR	THQL21100, (2) THQL1120, THQL2150GFT		2					42		

Metered

Top Feed






Previous Model Number ¹	Replacement Model Number ²	Receptacle	Circuit Protection	Amps	Spaces	Cabinet Size	Diagram	Unit Wt.	Std. Pkg.	UL Approved
R055C033	R155MBC033 NEW	R54UWR, 5-20R2GFCIWR	THQL2170, THQL1120, THQL2150GFT	100	—	9 x 30		27	1	UL, MEG
M076C033	M176MBC033 NEW	R54UWR, (2) 5-20R2GFCIWR	THQL21100, (2) THQL1120, THQL2150GFT		2	9 x 30		29		UL
R011C010	R111MBC010	(2) 5-20R2GFCIWR	THQL21100, (2) THQL1120		1	9 x 30		25		UL, MEG
R038C033	R138MBC033	6-20R, (2) 5-20R2GFCIWR	THQL21100, (2) THQL1120, THQL2120GFT		2	9 x 30		25		
R076C033	R176MBC033 NEW	R54UWR, (2) 5-20R2GFCIWR	THQL21100, (2) THQL1120, THQL2150GFT		2	9 x 30		29		UL

¹ RV only, does not include Service Entrance label.





² Only GE by ABB breakers can be installed.

Metered

Bottom Feed













Previous Model Number	Replacement Model Number	Receptacle	Circuit Protection	Amps	Spaces	Cabinet Size	Diagram	Unit Wt.	Std. Pkg.	UL Approved
M055C033U	M155MBC033U NEW	R54UWR, 5-20R2GFCIWR	THQL2170, THQL1120, THQL2150GFT2	70	—	9 x 30		27	1	UL
M055GP6033	M155MBGP6033 NEW	BR54UWR, 5-20R2WR	THQL2170, THQL1120GFT, THQL2150GFT		—	9 x 30		51		
R055C033U	R155MBC033U NEW	R54UWR, 5-20R2GFCIWR	THQL2170, THQL1120, THQL2150GFT2		—	9 x 30		27		
R011C010U	R111MBC010U	(2) 5-20R2GFCIWR	THQL21100, (2) THQL1120	100	1	9 x 30		25	UL, MEG	
R038C033U	R138MBC033U	6-20R, (2) 5-20R2GFCIWR	THQL21100, (2) THQL1120, THQL2120GFT		2	9 x 30		25		

Unmetered

Previous Model Number	Replacement Model Number	Receptacle	Circuit Protection	Amps	Spaces	Cabinet Size	Diagram	Unit Wt.	Std. Pkg.	UL Approved
U055C033	NEW U155MBC033	R54UWR, 5-20R2GFCI	THQL2170, THQL1120, THQL2150GFT	70	—	9 x 17		30	1	UL
U038C033	NEW U138MBC033	6-20WR, (2) 5-20R2GFCI	THQL21100, (2) THQL1120, THQL2120GFT	100	2	14 x 21		38		
U038G033	NEW U138MBG033	(2) 6-20WR, (2) 5-20R2WR	THQL21100, THQL1120GFT, THQL2120GFT		2	14 x 21		40		
U076C033	NEW U176MBC033	R54UWR, (2) 5-20R2GFCI	THQL21100, (2) THQL1120, THQL2150GFT		2	14 x 21		42		

TECHNICAL DATA

Temporary Power

Model Number	Replacement Parts Meter Socket	Cabinet Size	Enclosure Style	Cabinet Dimensions (inches)			Knockout Figure	Hub	kAIC
				Height (A)	Width (B)	Depth (C)			
M138CB2033	—	14 x 26		26-3/5	14-1/2	4-4/5			
M155MBC033U	—	9 x 30U		29-1/2	9-1/2	5			
M155MBGP6033	MSM100930	9 x 30		30	9-3/4	5-3/16			
M176MBC033	MSM100930	9 x 30		29-5/8	9-5/16	3-5/8		Yes	10
R101CB2010	MW200R	14 x 26		26-1/4	14-3/4	4-9/16			
R111CB2C010	MW200R	14 x 26		26-3/5	14-1/2	4-4/5			

Knockout Key

- B = 1", 1-1/4", 1-1/2"
- D = 3/4", 1", 1-1/4"
- E = 9/32"
- F = 1/2"
- G = 1/2", 3/4", 1"
- N = 1/2", 3/4", 1", 1-1/4", 1-1/2", 2"
- W = 1/2", 3/4", 1", 1-1/4", 2"
- X = 1/2", 3/4", 1-1/4", 1-1/2", 2", 2-1/2"
- Y = 1-1/4", 1-1/2", 2", 2-1/2", 3"













TECHNICAL DATA (continued)

Model Number	Replacement Parts Meter Socket	Cabinet Size	Enclosure Style	Cabinet Dimensions (inches)			Knockout Figure	Hub	kAIC
				Height (A)	Width (B)	Depth (C)			
R111MBC010	MSR100930	9 x 30		30	9-3/4	5-3/16			
R111MBC010U	MSM100EZ	9 x 30U		30	9-3/4	5-3/16			
R138CB2033	MW200RI	14 x 26		26-3/5	14-1/2	4-4/5			
R138MBC033	MSR100930	9 x 30		30	9-3/4	5-3/16		Yes	10
R138MBC033U	MSM100EZ	9 x 30U		30	9-3/4	5-3/16			
NEW R155MBC033	MSR100930	9 x 30		29-1/2	9-1/2	5			
NEW R155MBC033U	MSM100EZ	9 x 30U		29-1/2	9-1/2	5			

Knockout Key

B = 1", 1-1/4", 1-1/2" N = 1/2", 3/4", 1", 1-1/4", 1-1/2", 2"
 D = 3/4", 1", 1-1/4" W = 1/2", 3/4", 1", 1-1/4", 2"
 E = 9/32" X = 1/2", 3/4", 1-1/4", 1-1/2", 2", 2-1/2"
 F = 1/2" Y = 1-1/4", 1-1/2", 2", 2-1/2", 3"
 G = 1/2", 3/4", 1"

TECHNICAL DATA (continued)

Model Number	Replacement Parts Meter Socket	Cabinet Size	Enclosure Style	Cabinet Dimensions (inches)			Knockout Figure	Hub	kAIC
				Height (A)	Width (B)	Depth (C)			
R176CB2033	MW200RI	14 x 26		26-3/5	14-1/2	4-4/5			
NEW R176MBC033	MSR100930	9 x 30		29-5/8	9-5/16	3-5/8			
NEW U138MBC033	—	14 x 21		21-5/8	14-1/2	5		Yes	10
NEW U138MBG033	—	14 x 21		21-5/8	14-1/2	5			
NEW U155MBC033	—	9 x 17		17-1/16	9-1/16	5-3/16			
NEW U176MBC033	—	14 x 21		21-1/16	14-1/2	6-5/8			

Knockout Key

- B = 1", 1-1/4", 1-1/2"
- D = 3/4", 1", 1-1/4"
- E = 9/32"
- F = 1/2"
- G = 1/2", 3/4", 1"
- N = 1/2", 3/4", 1", 1-1/4", 1-1/2", 2"
- W = 1/2", 3/4", 1", 1-1/4", 2"
- X = 1/2", 3/4", 1-1/4", 1-1/2", 2", 2-1/2"
- Y = 1-1/4", 1-1/2", 2", 2-1/2", 3"

Midwest Electric Products
Quality Weatherproof Electrical Equipment

305 Gregson Drive • Cary, NC 27511
 Customer Service: 866.685.0577 • Fax: 804.965.1041

midwestelectric.com

© 2024 Midwest Electric Products | 1TQC153600E0001 Rev.F June2024

Information provided is subject to change without notice. Please verify all details with Midwest Electric Products. All values are design or typical values when measured under laboratory conditions, and Midwest makes no warranty or guarantee, express or implied, that such performance will be obtained under end-use conditions.

